iU6399A

3-Phase BLDC Motor Controller

Datasheet Rev. 0.4

1. Description

The iU6399A is a 3-phase BLDC motor controller IC integrated with various peripherals to realize sensor or sensor-less BLDC motors application, including FOC. The logic input is compatible with standard CMOS output. It features the flexibility to adjust various motor parameters and complete protection such as over current, over voltage and under voltage lockout. Moreover, its operation current is only ~10mA and a low power stop mode can further save the power when the motor stops rotating.

2. Features


- Three-Phase BLDC Motor Controller
- Operating Supply Voltage from 7V to 24V
- Integrated Current Amplifier x 2
- Programmable Locked Rotor and Restart Timing
- Programmable Soft Start Timing
- Complete Protection OCP/OVP/UVLO
- TSSOP-24 Package

3. Applications

- BLDC Motor Driver

© 2026 inergy Technology Inc. All rights reserved.

4. Pin Assignments



5. Marking Information

Product Name	Marking
iU6399A	 X: Date code

6. Ordering Code

Ordering Code
iU6399A


© 2026 inergy Technology Inc. All rights reserved.

7. Pin Definitions

Pin No.	Symbol	Description
1	NRST	External RESET
2	Data	Data Input
3	Clock	Clock Input
4	LOW	PWM 3 Complementary Output
5	HOW	PWM 3 Output
6	LOV	PWM 2 Complementary Output
7	HOV	PWM 2 Output
8	LOU	PWM 1 Complementary Output
9	HOU	PWM 1 Output
10	VDD	Self Logic 5V Power
11	VSS	Ground
12	VIN	Power Input
13	PWM	PWM Input
14	Hall	Hall Input
15	OPA2 in+	OPAMP2 Positive Input
16	OPA2 in-	OPAMP2 Negative Input
17	OPA2_out	OPAMP2 Output
18	OPA1 in+	OPAMP1 Positive Input
19	OPA1 in-	OPAMP1 Negative Input
20	OPA1_out	OPAM1 Output
21	I_lim	Average Current Detection
22	OCP	Over Current Protection
23	FG	FG Output
24	OVP	Over Voltage Protection

© 2026 inergy Technology Inc. All rights reserved.

8. Function Block Diagram



© 2026 inergy Technology Inc. All rights reserved.

9. Electrical Characteristics

9.1 Absolute Maximum Ratings

Absolute maximum ratings indicate sustained limits beyond which damage to the device may occur. All voltage parameters are absolute voltages referenced to GND, all currents are defined positive into any lead. The thermal resistance and power dissipation ratings are measured under board mounted and still air conditions.

Symbol	Parameter	Min.	Max.	Unit
VIN	Power Input	- 0.3	28	V
I/O Pin	Logic Input Voltage	- 0.3	VDD + 0.3	V
T_J	Junction Temperature	- 40	125	℃
T_S	Storage Temperature	- 55	150	

9.2 Recommended Operating Conditions

Symbol	Parameter	Min.	Max.	Unit
VIN	Power Input	7	24	V
I/O Pin	Logic Input Voltage	0	VDD + 0.3	V
T_A	Ambient Temperature (*Note)	- 40	105	℃

*Note：Please do not exceed Tj limitation

© 2026 inergy Technology Inc. All rights reserved.

9.3 D.C. Characteristics

Symbol	Conditions			Min.	Typ.	Max	Unit
	Mode	f_{HCLK}	Conditions				
IDD	Operation Mode Internal Clock	60MHz	All Peripherals Enabled	-	8.61	-	mA
			All Peripherals Disabled	-	7.08	-	mA
		40KHz	All Peripherals Enabled	-	1.02	-	mA
			All Peripherals Disabled	-	1.00	-	mA
	Sleep Mode, Internal Clock	60MHz	All Peripherals Enabled	-	3.52	-	mA
			All Peripherals Disabled	-	2.25	-	mA
		40KHz	All Peripherals Enabled	-	1.00	-	mA
			All Peripherals Disabled	-	1.00	-	mA
	Stop Mode	-	Enter Stop Mode after Reset	-	110	-	uA

© 2026 inergy Technology Inc. All rights reserved.

9.4 A.C. Characteristics

9.4.1 High Speed Internal Oscillator (HSI) Characteristics

Symbol	Parameter	Conditions	Min.	Typ.	Max	Unit
f_{HSI}	Frequency	-	-	60	-	MHz
ACC_{HSI}	Accuracy of HSI Oscillator	T_A = -40°C ~ 105°C	-2.5	-	+2.5	%
		T_A = -10°C ~ 85°C	-1.5	-	+1.5	%
		T_A = 25°C	-1	-	+1	%


9.4.2 Low Speed Internal Oscillator (LSI) Characteristics

Symbol	Parameter	Conditions	Min.	Typ.	Max	Unit
F_{LSI}	Frequency	T_A = -40°C ~ 105°C	20	40	60	KHz
$tsu_{(LSI)}$	LSI Oscillator Start-up Time	-	-	-	300	us
$IDD_{(LSI)}$	Power Consumption of LSI Oscillator	-	-	0.34	-	uA

9.4.3 Power-up and Power-down Characteristics

Symbol	Conditions	Min.	Typ.	Max	Unit
t_{VDD}	VDD Rising Time tr	300	-	50000	us
	VDD Falling Time tf	300	-	50000	
V_{ft}	Power-down Threshold Voltage	0	-	-	mV

Note 1：Derived from overall evaluation, not tested in production.
Note 2：The on-chip VDD waveform during power-down should follow the tr and tf stages as shown in the waveform diagram below.
Note 3：The chip should be powered up from 0V to ensure reliable power-up.



9.4.4 Low-Power Mode Wake-up Time

Symbol	Conditions	Min.	Typ.	Max	Unit
$t_{WUSLEEP}$	Wake-up from Sleep Mode (System Clock is HSI)	-	1.5	-	us
t_{WUSTOP}	Wake-up from Stop Mode (System Clock is HSI)	-	65	-	us

© 2026 inergy Technology Inc. All rights reserved.

9.5 Input / Output Characteristics

Symbol	Parameter	Conditions	Min.	Typ.	Max	Unit
V_{IL}	Input low-level voltage	5V CMOS port	-	-	0.3 * VDD	V
V_{IH}	Input high-level voltage	5V CMOS port	0.7 * VDD	-	-	V
V_{hy}	I/O pin Schmitt trigger voltage hysteresis	5V	0.1 * VDD	0.60	-	V
I_{lkg}	Input leakage current	5V	-1	-	1	μA
R_{PU}	Weak pull-up equivalent resistor	5V VIN = VSS	50	60	75	kΩ
R_{PD}	Weak pull-down equivalent resistor	5V VIN = VSS	50	60	75	kΩ
C_{IO}	I/O pin capacitance	-	-	-	10	pF

Symbol	Parameter	Conditions	Typ.	Unit
V_{OL}	Output low level	$\|I_{IO}\|$ = 6mA , VDD = 5V	0.11	V
V_{OH}	Output high level		4.83	
V_{OL}	Output low level	$\|I_{IO}\|$ = 8mA , VDD = 5V	0.15	
V_{OH}	Output high level		4.78	
V_{OL}	Output low level	$\|I_{IO}\|$ = 20mA , VDD = 5V	0.38	
V_{OH}	Output high level		4.4	

© 2026 inergy Technology Inc. All rights reserved.

9.6 POR / PVD Electrical Characteristics

Symbol	Parameter	Conditions	Min.	Typ.	Max	Unit
V_{PVD}	Level Selection for Programmable Voltage Detector	Rising Edge: Level 1	-	2.4	-	V
		Falling Edge: Level 1	-	2.3	-	V
		Rising Edge: Level 2	-	2.7	-	V
		Falling Edge: Level 2	-	2.6	-	V
		Rising Edge: Level 3	-	3.0	-	V
		Falling Edge: Level 3	-	2.9	-	V
		Rising Edge: Level 4	-	3.3	-	V
		Falling Edge: Level 4	-	3.2	-	V
		Rising Edge: Level 5	-	3.6	-	V
		Falling Edge: Level 5	-	3.5	-	V
		Rising Edge: Level 6	-	3.9	-	V
		Falling Edge: Level 6	-	3.8	-	V
		Rising Edge: Level 7	-	4.2	-	V
		Falling Edge: Level 7	-	4.1	-	V
		Rising Edge: Level 8	-	4.5	-	V
		Falling Edge: Level 8	-	4.4	-	V
		Rising Edge: Level 9	-	4.8	-	V
		Falling Edge: Level 9	-	4.7	-	V
V_{POR}	Power-on Reset Threshold	-	-	2.2	-	V
$V_{hyst_POR/PDR}$	POR/PDR Hysteresis	-	-	60	-	mV
$T_{RSTTEMPO}$	Reset Duration	-	-	1.84	-	ms

© 2026 inergy Technology Inc. All rights reserved.

9.7 A/D Converter Electrical Characteristics

Symbol	Parameter	Conditions	Min.	Typ.	Max	Unit
V_{DD}	Supply Voltage	-	2.5	-	5.5	V
f_{ADC}	ADC Clock Frequency	VDD ≥ 2.5V	-	-	15	MHz
f_S	Sampling Rate	12bits; VDD ≥ 2.5V	-	-	1	MHz
f_{TRIG}	External trigger frequency	12bits; f_{ADC} = 15MHz	-	-	1	MHz
		12bits	-	-	15	1/ fADC
R_{AIN}	External Input Impedance	-	See the formula below			KΩ
R_{ADC}	Sampling switch resistance	-	-	-	1.5	KΩ
C_{ADC}	Internal sampling and holding capacitance	-	-	-	5	pF
t_{STAB}	Power-up Time	-	-	-	10	μS
t_{lat}	Injection-Trigger Conversion Delay	-	-	-	512	1/fADC
t_{latr}	Regular-Trigger Conversion Delay	-	-	-	512	1/fADC
ts	Sampling Time	f_{ADC} = 15MHz	0.167	-	16.03	μS
t_{CONV}	Total Conversion Time (including Sampling Time)	12bits; f_{ADC}=15MHz	1	-	16.87	μS
ENOB	Effective Number of Bits	12bits; VDD ≥ 3.3V; f_{ADC} = 15MHz	-	10.9	-	bit

Note: For external triggering, a delay of 1/f_{ADC} must be added to the timing

Input Impedance Table

$$R_{AIN} < \frac{T_S}{f_{ADC} \times C_{ADC} \times ln(2^{n+2})} - R_{ADC}$$

The above formula is used to determine the maximum external impedance to ensure that the error is less than 1/4 LSB. Here, n = 12 (representing 12-bit resolution) and it is measured at f_{ADC} = 15MHz.

Symbol	Parameter	Conditions	Typ.	Unit
ET	Overall Error	f_{PCLK1}=60MHz, f_{ADC}=15MHz, R_{AIN}<0.1KΩ, VDD=5V, T_A=25°C	-4.7 to +3.4	LSB
EO	Offset Error		-1.9 to +2.8	LSB
EG	Gain Error		-0.4 to +1.6	LSB
ED	Differential Linearity Error		-1.0 to +0.4	LSB
EL	Integral Linearity Error		-2.2 to +3.4	LSB

© 2026 inergy Technology Inc. All rights reserved.

9.8 Operational Amplifier Electrical Characteristics

Symbol	Parameter	Conditions	Min.	Typ.	Max	Unit
V_{DD}	Supply Voltage	-	2.5	-	5.5	V
V_{OFFSET}	Input Bias Voltage	-	-	1	-	mV
I_{LOAD}	Drive Current	Drive current (sinking current) (VDD=5V, VOUT=1V)	-	-	15	mA
C_{LOAD}	Capacitive Load	-	-	-	30	pF
CMRR	Common Mode Rejection Ratio	-	-	80	-	dB
PSRR	Power Supply Rejection Ratio	-	-	80	-	dB
GBW	Gain-Bandwidth Product	-	-	12	-	MHz
SR	Slew Rate	-	-	7	-	V/us
GOL	Open-loop Gain	-	90	110	120	dB

9.9 Comparator Electrical Characteristics


Symbol	Parameter	Register Configuration	Min.	Typ.	Max	Unit
t_{HYST}	Hysteresis	00(hysteresis), high power	-	0	-	mV
		00(hysteresis), low power	-	0	-	mV
		01(hysteresis), high power	15	22	43	mV
		01(hysteresis), low power	13	15	23	mV
		10(hysteresis), high power	32	45	92	mV
		10(hysteresis), low power	25.2	32	46.7	mV
		11(hysteresis), high power	55	85	182	mV
		11(hysteresis), low power	25.5	60	83.9	mV
V_{OFFSET}	Offset Voltage	-		+/-6	+/-10.4	mV
t_{DELAY}	Propagation Delay Note1	00（high power）	3.7	10.7	43	ns
		01（medium power）	10.5	34.9	83	ns
		10（low power）	13.8	49	114	ns
		11（ultra-low power）	22.2	86	194.5	ns
Iq	Average Operating Current	00（high power）	6.5	45	205.4	μA
		01（medium power）	3.3	21.7	81.3	μA
		10（low power）	2.6	15.3	59.6	μA
		11（ultra-low power）	1.7	8.8	35.3	μA

Note1 : Time difference between 50% output transistor and input transition.

© 2026 inergy Technology Inc. All rights reserved.

10. Package Information

TSSOP-24 Outline Dimensions



SYMBOL	Dimension in mm		
	MIN.	NOM.	MAX.
A	–	–	1.20
A1	0.05	–	0.15
A2	0.80	1.00	1.05
b	0.19	–	0.30
c	0.09	–	0.20
D	7.70	7.80	7.90
E1	4.30	4.40	4.50
E	6.40 BSC		
e	0.65 BSC		
L	0.45	0.60	0.75
θ	0°	–	8°

© 2026 inergy Technology Inc. All rights reserved.

Important Notice

1. inergy Technology Inc. reserves the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete.

2. The Products of inergy Technology Inc. have been tested, verified and passed by our specifications and standards, and are 100% inspected before delivery from the factory. It is strongly recommended that the customers shall perform verifications of the functionality, compatibility, and reliability of the environment or platform that you used. inergy Technology Inc. would not be liable for or guarantee anything that is related to the functionality, compatibility, and reliability of the environment or platform used by the customers.

© 2026 inergy Technology Inc. All rights reserved.